

PERIODIC SOLUTIONS OF THE EXTENDED DUFFING-VAN DER POL OSCILLATOR

RODRIGO D. EUZÉBIO^{1,2} AND JAUME LLIBRE¹

ABSTRACT. In this paper some aspects on the periodic solutions of the extended Duffing-Van der Pol oscillator are discussed. Doing different rescaling of the variables and parameters of the system associated to the extended Duffing-Van der Pol oscillator we show that it can bifurcate one or three periodic solutions from a 2-dimensional manifold filled by periodic solutions of the referred system. For each rescaling we exhibit concrete values for which these bounds are reached. Beyond that we characterize the stability of some periodic solutions. Our approach is analytical and the results are obtained using averaging theory and some algebraic techniques.

1. INTRODUCTION

1.1. Setting the problem. A large number of non-autonomous chaotic phenomena in physics, engineering, mechanics, biology among others are described by second-order differential systems of the form

$$(1) \quad \ddot{x} = g(x, \dot{x}, t) + \gamma(t),$$

where $g(x, \dot{x}, t)$ is a continuous function and $\gamma(t)$ is some external force. For instance, in biology system (1) models the FHN neuron oscillator and in the engineering system (1) it is a model to the horizontal platform system.

The specific topic addressed in this paper concerns with other particular case of equation (1), namely, an extension of the forced Van der Pol equation with external excitation. Van der Pol's system also plays an important role in many applications in areas like engineering, biology, physics and seismology (see [2] and references therein).

The system associated with the forced Van der Pol equation with external excitation is characterized by system (1) with functions g and γ in the form

$$(2) \quad g(x, \dot{x}, t) = \rho_0(1 - x^2)\dot{x} - \frac{d}{dx}V(x), \quad \gamma(t) = \delta_0 \cos(\omega t),$$

where ρ_0 is the damping parameter, $V(x)$ is the potential function and δ_0 and ω are the amplitude and angular frequency of the driving force $\gamma(t)$, respectively. We assume that ρ_0 is non-negative and δ_0 and ω are positive.

2010 *Mathematics Subject Classification.* Primary 34C07, 34C15, 34C25, 34C29, 37C60.

Key words and phrases. Extended Duffing-Van der Pol oscillator, periodic solution, non-autonomous systems, averaging theory.

The potential $V(x)$ can be approximated by a finite Taylor expansion in series

$$V_2(x) = \frac{1}{2}\omega_0^2 x^2, \quad V_4(x) = \frac{1}{2}\omega_0^2 x^2 + \frac{1}{4}\alpha_0 x^4, \quad V_6(x) = \frac{1}{2}\omega_0^2 x^2 + \frac{1}{4}\alpha_0 x^4 + \frac{1}{6}\lambda_0 x^6,$$

where ω_0 and λ_0 are non-zero and α_0 is a real number.

Almost all papers on forced excited Van der Pol systems deal with the potential V_2 . However some papers concerning the potential V_4 have shown a lot of interesting behaviours (see [7], [12], [25], [27] and [28]). This case is usually referred as Duffing–Van der Pol oscillator or ϕ^4 –Van der Pol oscillator. Nevertheless more recently some papers were published taking into account the potential V_6 mainly addressing with the problem of chaos control (see [13], [17] and [22]). The dynamics considering the potential V_6 is more complex and rich than the corresponding cases considering the potentials V_2 and V_4 (see [24] and [26]). This is the case that we will regard. This case is quoted in the literature as extended Duffing–Van der Pol oscillator or ϕ^6 –Van der Pol oscillator.

In this paper we will give an analytical treatment to system (1) in order to study its periodic solutions considering functions (2) and the potential V_6 . Indeed, calling $y = \dot{x}$ we obtain

$$(3) \quad \begin{aligned} \dot{x} &= y, \\ \dot{y} &= -\omega_0^2 x + \rho_0 y - \alpha_0 x^3 - \rho_0 x^2 y - \lambda_0 x^5 + \delta_0 \cos(\omega t). \end{aligned}$$

System (3) becomes simpler if we perform a rescaling $s = \omega t$ in the time t and another one $y = \omega_0 Y$ in the spatial variable y . In fact, calling again the new time s by t and the variable Y by y , after the rescaling we have

$$(4) \quad \begin{aligned} \dot{x} &= y, \\ \dot{y} &= -x + \rho y - \alpha x^3 - \rho x^2 y - \lambda x^5 + \delta \cos t, \end{aligned}$$

where the new parameters ρ , α , λ and δ are the respective old ones divided by ω_0^2 . The study of the periodic solutions of the non-linear non-autonomous 2π –periodic differential system (4) will be the objective of this paper.

When α , λ and δ are zero equation (4) is referred as unforced Van der Pol equation and has a unique stable periodic solution for ρ positive. Furthermore, if ρ is large this periodic solution remains and it describes a periodic oscillatory behaviour called relaxation oscillation. On the other hand, by considering δ non-zero, system (4) can present nonlinear attractors from simple periodic solutions up to multiperiodicity and chaos. In [10] we can find a didactical discussion about these objects and some results using classical techniques are obtained for a special case of system (4) using particular values of ρ , δ , ω and initial conditions.

There exists an exhaustive list of papers in the literature studying the properties of system (4) when δ is zero. For δ positive many open questions remain mainly due to the difficulty of integrate the system. In particular, in [19] the authors study some aspects of robust practical synchronization

for system (1) and apply the results to a particular case of system (4). In the same direction, in [14] the author investigate synchronization processes between chaotic attractors considering $\alpha = \lambda = 0$ in system (4). In [2] and [11] it is studied many aspects of system (4) for the case where α and λ are zero and ρ is large. Furthermore in [8] the authors provide sufficient conditions to the existence of one periodic solution under some analytical hypotheses for a general forced Van der Pol system considering ρ equal to zero.

Periodic solutions for system (4) were found in [17], where the authors investigate chaos control. Besides, in [5] and [6] were obtained results on the existence of periodic solutions for an autonomous special case of the extended Duffing-Van der Pol oscillator. In [16], [30] and [31] we also can find some results on systems similar to system (4).

In this paper we are concerned with periodic solutions of system (4). We will present sufficient conditions in order that this system possess one or three periodic solution and we will provide conditions on the parameters ρ , α , λ and δ for which these bounds are realizable. In Addition we will prove that it is not possible to obtain different bounds of periodic solutions using the methodology presented in this paper.

The phase space of our non-autonomous differential system is (x, y, t) and its Poincaré map is defined in the (x, y) -space. When possible the stability of the periodic solutions will be studied. As usual a periodic solution is *stable* if the eigenvalues of the fixed point associated to its Poincaré map have negative real part, otherwise there periodic solution is *unstable*. Inside the unstable periodic solutions there are two types. The unstable saddle periodic solutions having an eigenvalue with negative real part and the other with positive real part, and the repeller with both eigenvalues having negative real part.

We should note that the method used here for studying periodic solutions can be applied to any periodic non-autonomous differential system as done in [9] and [18]. In these papers the authors applied the method used in this paper in order to guarantee the existence of periodic solutions in a periodic FitzHugh-Nagumo system and in the Vallis system, respectively.

The paper is organized as follows. In subsection 1.2 the main results are stated and compared with other results. Also, some important points on the results are clarified. In subsection 2.1 we prove the results. In subsection 2.2 some aspects on the results are pointed out. Lastly, section 3 is devoted to give a brief summary of the results that we use from averaging theory.

1.2. Statement of the main results. In this section we present our results. We will behave under an analytical approach and for this reason the results are valid for a large range of the parameters of system (4), different from the major part of the results dealing with numerical techniques. In

addition, it is important to note that we are concerned with harmonic solutions in the sense that they do not bifurcate from periodic solutions with multiple period.

We have the following results.

Theorem 1. *Consider $\varepsilon > 0$ sufficiently small, $(\rho, \delta, \alpha, \lambda) = (\varepsilon r, \varepsilon d, \varepsilon^{n_2} a, \varepsilon^{n_3} \ell)$ with $n_2, n_3 > 1$ and $81d^2 > 48r^2 > 0$. Then system (4) has a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that*

$$(x(0, \varepsilon), y(0, \varepsilon)) \rightarrow \left(0, \frac{2(36r)^{1/3}}{3\Gamma} + \frac{1}{3} \left(\frac{6}{r} \right)^{1/3} \Gamma \right),$$

when $\varepsilon \rightarrow 0$, where $\Gamma = \left(9d + \sqrt{81d^2 - 48r^2} \right)^{1/3}$. Moreover, for r sufficiently small this periodic solution is stable.

Theorem 2. *Consider $\varepsilon > 0$ sufficiently small, $(\alpha, \delta, \rho, \lambda) = (\varepsilon a, \varepsilon d, \varepsilon^{n_1} r, \varepsilon^{n_3} \ell)$ with $n_1, n_3 > 1$ and $\alpha \neq 0$. Then system (4) has a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that*

$$(x(0, \varepsilon), y(0, \varepsilon)) \rightarrow \left(\left(\frac{4d}{3a} \right)^{1/3}, 0 \right),$$

when $\varepsilon \rightarrow 0$.

Theorem 3. *Consider $\varepsilon > 0$ sufficiently small and $(\lambda, \delta, \rho, \alpha) = (\varepsilon \ell, \varepsilon d, \varepsilon^{n_1} r, \varepsilon^{n_2} a)$ with $n_1, n_2 > 1$. Then system (4) has a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that*

$$(x(0, \varepsilon), y(0, \varepsilon)) \rightarrow \left(\left(\frac{8d}{5\ell} \right)^{1/5}, 0 \right),$$

when $\varepsilon \rightarrow 0$.

We remark that the stability of the periodic solutions of Theorems 2 and 3 cannot be decided with the real part of the eigenvalues of their Poincaré map because these real part are zero.

Theorem 4. *Consider $\varepsilon > 0$ sufficiently small and $(x, y, \rho, \delta, \alpha, \lambda) = (\varepsilon X, \varepsilon Y, \varepsilon r, \varepsilon^2 d, \varepsilon^{n_2} a, \varepsilon^{n_3} \ell)$ with $\rho \neq 0$. Then system (4) has a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that*

$$(x(0, \varepsilon), y(0, \varepsilon)) = \left(O(\varepsilon), -\frac{\delta}{\varepsilon \rho} + O(\varepsilon) \right),$$

when $\varepsilon \rightarrow 0$. Moreover this periodic solution is unstable.

Note that in Theorem 4 we have a periodic solution that comes from infinity. As far as we know this kind of behaviour also has not been observed in the papers concerned with system (4). Nevertheless this behaviour is common when we perform a rescaling in the parameters and variables as we made previously and can be observed also in papers [9] and [18].

Theorem 5. Consider $\varepsilon > 0$ sufficiently small, $(\alpha, \lambda, \delta, \rho) = (\varepsilon a, \varepsilon \ell, \varepsilon d, \varepsilon^{n_1} r)$ with $n_1 > 1$, $\alpha \lambda < 0$ and

$$D = \frac{53747712a^5 d^2}{78125\ell^7} + \frac{20480d^4}{\ell^4}.$$

Then system (4) has a 2π -periodic solution if $D = 0$ and three 2π -periodic solution if $D < 0$. Moreover, there are values of α , λ and δ that realize these number of periodic solutions.

Theorem 6. Consider $\varepsilon > 0$ sufficiently small, $(\rho, \alpha, \delta, \lambda) = (\varepsilon r, \varepsilon a, \varepsilon d, \varepsilon^{n_3} \ell)$ with $n_3 > 1$ and $-324a^4 r^2 - 9a^2 d^2 r^2 + 36a^2 r^4 - d^2 r^4 \neq 0$. Consider also the values

$$\begin{aligned} \Delta_1 &= 324a^4 + d^2 r^2 + 9a^2(d^2 - 4r^2), \\ \Delta_2 &= 2187a^4 d^4 + 27d^4 r^4 - 16d^2 r^6 + 18a^2(27d^4 r^2 - 72d^2 r^4 + 32r^6). \end{aligned}$$

The system

$$\begin{aligned} r x_0(-4 + x_0^2 + y_0^2) - 3a y_0(x_0^2 + y_0^2) &= 0, \\ 4d - r y_0(-4 + x_0^2 + y_0^2) - 3a x_0(x_0^2 + y_0^2) &= 0, \end{aligned}$$

has one solution (x_0^0, y_0^0) if $\Delta_1 \Delta_2 = 0$ or $\Delta_2 > 0$ and three solutions (x_0^i, y_0^i) if $\Delta_2 < 0$ for $i = 1, 2, 3$, all of them satisfying

$$27\alpha^2 ((x_0^i)^2 + (y_0^i)^2)^2 + \rho^2 (-4 + (x_0^i)^2 + (y_0^i)^2) (-4 + 3(x_0^i)^2 + 3(y_0^i)^2) \neq 0.$$

Then if $\Delta_1 \Delta_2 = 0$ or $\Delta_2 > 0$ system (4) has a 2π -periodic solution $(x^0(t, \varepsilon), y^0(t, \varepsilon))$ such that $(x^0(0, \varepsilon), y^0(0, \varepsilon)) \rightarrow (x_0^0, y_0^0)$ when $\varepsilon \rightarrow 0$. Additionally if $\Delta_2 < 0$ system (4) has three 2π -periodic solution $(x^i(t, \varepsilon), y^i(t, \varepsilon))$ such that $(x^i(0, \varepsilon), y^i(0, \varepsilon)) \rightarrow (x_0^i, y_0^i)$ when $\varepsilon \rightarrow 0$ for $i = 1, 2, 3$. Moreover there are values of ρ , α and δ for which these number of periodic solutions is reached.

Theorem 7. Consider $\varepsilon > 0$ sufficiently small, $(\alpha, \rho, \lambda, \delta) = (\varepsilon a, \varepsilon r, \varepsilon \ell, \varepsilon d)$, $\alpha\rho \neq 0$, $(r^2 - 3a^2)(r^2 - 9a^2) \neq 0$ and

$$\begin{aligned} C &= 4(3a + 10\ell)(540a^3\ell - 9a^2(d^2 - 600\ell^2) - 120a\ell(d^2 - 150\ell^2) + \\ &\quad 50\ell^2(-7d^2 + 400\ell^2))r^6 + 6(a + 5\ell)(6a - d + 20\ell)(6a + d + 20\ell)r^8 \neq 0, \\ D &= 2066242608a^{14}d^6 - 3125d^8r^{12} - 531441a^{12}(3125d^8 + 96d^6r^2 + \\ &\quad 1536d^4r^4 - 1024d^2r^6) + 354294a^{10}(3125d^8r^2 + 616d^6r^4 - 1600 \\ &\quad d^4r^6) + 18a^2r^{10}(9375d^8 + 5000d^6r^2 - 88000d^4r^4 + 102400d^2r^6 - \\ &\quad 32768r^8) + 2916a^6r^6(15625d^8 + 11700d^6r^2 - 45632d^4r^4 + 23552 \\ &\quad d^2r^6 - 2048r^8) - 6561a^8r^4(46875d^8 + 24832d^6r^2 - 66816d^4r^4 + \\ &\quad 12288d^2r^6 + 4096r^8) + 81a^4r^8(-46875d^8 - 36000d^6r^2 + 275200d^4 \\ &\quad r^4 - 246784d^2r^6 + 61440r^8). \end{aligned}$$

The system

$$\begin{aligned} 2rx_0(-4 + x_0^2 + y_0^2) - y_0(x_0^2 + y_0^2)(6a + 5\ell(x_0^2 + y_0^2)) &= 0, \\ 8d + 8ry_0 - (x_0^2 + y_0^2)(6ax_0 + 2ry_0 + 5\ell x_0(x_0^2 + y_0^2)) &= 0, \end{aligned}$$

has one solution (x_0^0, y_0^0) if $D < 0$ and three solutions (x_0^i, y_0^i) if $D > 0$ for $i = 1, 2, 3$, all of them satisfying

$$\begin{aligned} 4\rho^2(-4 + (x_0^i)^2 + (y_0^i)^2)(-4 + 3(x_0^i)^2 + 3(y_0^i)^2) + ((x_0^i)^2 + (y_0^i)^2)^2(6\alpha + \\ \rho\lambda((x_0^i)^2 + (y_0^i)^2))(18\alpha + 25\lambda(x_0^i)^2 + 3(y_0^i)^2) \neq 0. \end{aligned}$$

Then, if $D < 0$ system (4) has a 2π -periodic solution $(x^0(t, \varepsilon), y^0(t, \varepsilon))$ such that $(x^0(0, \varepsilon), y^0(0, \varepsilon)) \rightarrow (x_0^0, y_0^0)$ when $\varepsilon \rightarrow 0$. Furthermore, if $D > 0$ system (4) has three 2π -periodic solution $(x^i(t, \varepsilon), y^i(t, \varepsilon))$ such that $(x^i(0, \varepsilon), y^i(0, \varepsilon)) \rightarrow (x_0^i, y_0^i)$ when $\varepsilon \rightarrow 0$ for $i = 1, 2, 3$. Moreover, there are values of α, ρ, λ and δ which realizes the number of these periodic solutions.

Theorem 8. Consider $\varepsilon > 0$ sufficiently small, $(\rho, \lambda, \delta, \alpha) = (\varepsilon r, \varepsilon \ell, \varepsilon d, \varepsilon^{n_2} a)$ with $n_2 > 1$. Consider the numbers

$$C = 4000d^3\ell^3r^4 + 7200000d\ell^5r^4 + 60d^3\ell r^6 + 72000d\ell^3r^6 + (50d^4\ell^2r^4 - 220000d^2\ell^4r^4 - 8000000\ell^6r^4 - 2800d^2\ell^2r^6 + 160000\ell^4r^6 - 6d^2r^8 + 2400\ell^2r^8),$$

$$N_2 = \frac{-4500\ell^2r^4 + 3r^6}{3125d^2\ell^4},$$

$$N_3 = 5859375d^4\ell^6 + 18750000d^2\ell^6r^2 + 87500\ell^4(-7d^2 + 1200\ell^2)r^4 + 25\ell^2(-7d^2 + 155600\ell^2)r^6 + 15600\ell^2r^8 + 9r^{10},$$

$$N_4 = 1171875d^8\ell^6(1250000\ell^4 + 8500\ell^2r^2 + r^4) - 2500d^6\ell^4(312500000000\ell^8 + 5343750000\ell^6r^2 + 74625000\ell^4r^4 + 358375\ell^2r^6 + 69r^8) - 3000d^4\ell^2r^2(218750000000\ell^{10} - 21625000000\ell^8r^2 - 686625000\ell^6r^4 - 3715000\ell^4r^6 - 650\ell^2r^8 - 3r^{10}) - 1600\ell^2r^6(400000000000\ell^{10} - 144900000000\ell^8r^2 - 2817000000\ell^6r^4 - 8880000\ell^4r^6 + 38700\ell^2r^8 + 27r^{10}) + 12d^2r^4(-5000000000000\ell^{12} - 3225000000000\ell^{10}r^2 - 662400000000\ell^8r^4 - 2803000000\ell^6r^6 + 5410000\ell^4r^8 + 19200\ell^2r^{10} + 9r^{12})$$

$$N_5 = 48828125d^8\ell^6 - 4687500d^6\ell^4r^4 + 6400\ell^2r^{10}(1600\ell^2 + r^2) - 16d^2r^8(2000000\ell^4 + 2900\ell^2r^2 + r^4) + d^4r^6(27500000\ell^4 + 60000\ell^2r^2 + 27r^4)$$

$$M_5 = -25d^4\ell^2 + d^2(110000\ell^4 + 1400\ell^2r^2 + 3r^4) + 400(10000\ell^6 - 200\ell^4r^2 - 3\ell^2r^4),$$

where $CM_5 \neq 0$. The system

$$\begin{aligned} 2rx_0(-4 + x_0^2 + y_0^2) - 5\ell y_0(x_0^2 + y_0^2)^2 &= 0, \\ 8d - 2ry_0(-4 + x_0^2 + y_0^2) - 5\ell x_0(x_0^2 + y_0^2)^2 &= 0, \end{aligned}$$

has one solution (x_0^0, y_0^0) if $N_2 \leq 0$, $N_3 \geq 0$ or $N_4 \geq 0$ and $N_5 > 0$ and three solutions (x_0^i, y_0^i) if $N_5 < 0$ for $i = 1, 2, 3$, all of them satisfying

$$125\lambda^2((x_0^i)^2 + (y_0^i)^4) + 4\rho^2(-4 + (x_0^i)^2 + (y_0^i)^2)(-4 + 3(x_0^i)^2 + 3(y_0^i)^2) \neq 0.$$

Hence, if $N_2 \leq 0$, $N_3 \geq 0$ or $N_4 \geq 0$ and $N_5 > 0$, then system (4) has a 2π -periodic solution $(x^0(t, \varepsilon), y^0(t, \varepsilon))$ such that $(x^0(0, \varepsilon), y^0(0, \varepsilon)) \rightarrow (x_0^0, y_0^0)$ when $\varepsilon \rightarrow 0$. If $N_5 < 0$ then system (4) has three 2π -periodic solution $(x^i(t, \varepsilon), y^i(t, \varepsilon))$ such that $(x^i(0, \varepsilon), y^i(0, \varepsilon)) \rightarrow (x_0^i, y_0^i)$ when $\varepsilon \rightarrow 0$ for $i = 1, 2, 3$. Moreover, there are values of ρ , λ and δ for which system (4) has one or three periodic solutions.

We note that in Theorems 5, 6, 7 and 8 we do not say anything about the kind of stability of the periodic solutions because we do not have the explicit expressions of the real part of the eigenvalues of their Poincaré maps.

We remark that the periodic solutions provided in Theorems 1 until 8 exist when we take small values for the parameters of system (4) obeying some relations among them. For instance Theorem 1 states the existence of one periodic solution for system (4) if each parameter of this system is small and α and λ are much smaller than ρ and δ . This assertion becomes more clear if we observe the replacement done in each theorem and taking into account that ε is sufficiently small. As far as we know periodic solutions of system (4) whose parameters have this characteristic have not been observed in the literature. Besides, it seems that the simultaneous bifurcation of three harmonic periodic solutions in extended Duffing-Van der Pol system's is also new.

Furthermore we note that the periodic solutions presented in the present paper are different from those ones stated in [8]. Indeed, in the referred paper the authors ask for $V_6'(0) < 0$, and in our case we have $V_6'(0) = 0$.

2. PROOF AND DISCUSSION OF THE RESULTS

2.1. Proof of the results. In order to apply averaging theory described in section 3 in systems (4) we start performing a rescaling of the variables x and y and of the parameters ρ , α , λ and δ as follows.

$$(5) \quad \begin{aligned} x &= \varepsilon^{m_1} X, & y &= \varepsilon^{m_2} Y, \\ \rho &= \varepsilon^{n_1} r, & \alpha &= \varepsilon^{n_2} a, & \lambda &= \varepsilon^{n_3} \ell, & \delta &= \varepsilon^{n_4} d, \end{aligned}$$

where ε is positive and sufficiently small and m_i and n_j are non-negative integers, for $i = 1, 2$ and $j = 1, 2, 3, 4$. We recall that since $\delta > 0$, $\rho \geq 0$ and $\lambda \neq 0$ we have $d > 0$, $r \geq 0$ and $\ell \neq 0$.

In the new variables (X, Y) system (4) writes

$$(6) \quad \begin{aligned} \frac{dX}{dt} &= \varepsilon^{-m_1+m_2} Y, \\ \frac{dY}{dt} &= -\varepsilon^{m_1-m_2} X + \varepsilon^{n_1} r Y - \varepsilon^{2m_1+n_1} r X^2 Y - \varepsilon^{3m_1-m_2+n_2} a X^3 \\ &\quad - \varepsilon^{5m_1-m_2+n_3} \ell X^5 + \varepsilon^{-m_2+n_4} d \cos t. \end{aligned}$$

In order to have non-negative powers of ε we must impose the conditions

$$(7) \quad m_1 = m_2 = m, \quad \text{and} \quad n_4 \geq m,$$

where m is a non-negative integer.

Hence, with conditions (7) system (6) becomes

$$(8) \quad \begin{aligned} \frac{dX}{dt} &= Y, \\ \frac{dY}{dt} &= -X + \varepsilon^{n_1} r Y - \varepsilon^{2m+n_1} r X^2 Y - \varepsilon^{2m+n_2} a X^3 - \varepsilon^{4m+n_3} \ell X^5 \\ &\quad + \varepsilon^{-m+n_4} d \cos t. \end{aligned}$$

In this paper we will find periodic solutions of system (8) depending on the parameters r , a , ℓ and d and the powers m , n_i of ε , for $i = 1, 2, 3, 4$. Then we will go back through the rescaling (5) to ensure the existence of periodic solutions in system (4).

From now on we assume that the values n_1 , $m^2 + n_2^2$, $m^2 + n_3^2$ and $n_4 - m$ are positive and observe that considering these conditions each power of ε in system (8) becomes positive. The reason for a such assumption will be explained later on in section 2.2. Now we shall apply the averaging theory described in section 3. Thus following the notation of the mentioned section and denoting again the variables (X, Y) by (x, y) we have $\mathbf{x} = (x, y)^T$ and system (13) corresponding to system (8) can be written as

$$(9) \quad \dot{\mathbf{x}} = F_0(t, \mathbf{x}) = (y, -x)^T.$$

So the solution $\mathbf{x}(t, \mathbf{z}) = (x(t, \mathbf{z}), y(t, \mathbf{z}))$ of system (9) such that $\mathbf{x}(0, \mathbf{z}) = \mathbf{z} = (x_0, y_0)$ is

$$\begin{aligned} x(t, \mathbf{z}) &= x_0 \cos t + y_0 \sin t, \\ y(t, \mathbf{z}) &= y_0 \cos t - x_0 \sin t. \end{aligned}$$

It is clear that the origin of coordinates of \mathbb{R}^2 is a global isochronous center for system (9) whose circular periodic solutions starting on $\mathbf{z} = (x_0, y_0) \in \mathbb{R}^2$ are parametrized by the above functions $x(t, \mathbf{z})$ and $y(t, \mathbf{z})$. Therefore through every initial condition (x_0, y_0) in \mathbb{R}^2 passes a 2π -periodic solution of system (9).

Physically speaking system (9) models a simple harmonic oscillator and its solutions $(x(t, \mathbf{z}), y(t, \mathbf{z}))$ describe the wave behaviour of this oscillator. In this direction the problem of perturbation of the global center (9) is equivalent to the problem of perturbation of a simple harmonic oscillator introducing a damping parameter, as external force and considering a potential V by taking small values for ρ , α , λ and δ as stated in Theorems from 1 to 8.

We note that using the notation of section 3 the fundamental matrix $Y(t, \mathbf{z})$ of system (9) satisfying that $Y(0, \mathbf{z})$ is the identity of \mathbb{R}^2 writes

$$Y(t, \mathbf{z}) = \begin{pmatrix} \cos t & \sin t \\ -\sin t & \cos t \end{pmatrix}.$$

From the averaging theory we are interested in the simple zeros of the function

$$(10) \quad f(\mathbf{z}) = (f_1(\mathbf{z}), f_2(\mathbf{z})) = \int_0^{2\pi} Y^{-1}(t, \mathbf{z}) F_1(t, \mathbf{x}(t, \mathbf{z}, 0)) dt,$$

where $F_1(t, \mathbf{x})$ are the terms of order 1 on ε of the vector field associated to system (8)

$$(y, -x + \varepsilon^{n_1} r y - \varepsilon^{2m+n_1} r x^2 y - \varepsilon^{2m+n_2} a x^3 - \varepsilon^{4m+n_3} \ell x^5 + \varepsilon^{-m+n_4} d \cos t)^T.$$

Now we prove our results.

Proof of Theorem 1: Firstly we take $n_1 = n_4 = 1$, $m = 0$ and consider $n_2, n_3 > 1$. So the rescaling (5) becomes $(x, y, \rho, \delta, \alpha, \lambda) = (X, Y, \varepsilon r, \varepsilon d, \varepsilon^{n_2} a, \varepsilon^{n_3} d)$ and calling again (X, Y) by (x, y) we verify the hypotheses of Theorem 1. Now the vector field of system (4) becomes

$$(y, -x + \varepsilon r y - \varepsilon r x^2 y - \varepsilon^{n_2} a x^3 - \varepsilon^{n_3} \ell x^5 + \varepsilon d \cos t)^T.$$

Hence as we stated before the terms of order 1 in this vector field are given by $F_1(t, \mathbf{x}) = (0, r y - r x^2 y + d \cos t)$. Then since $\mathbf{z} = (x_0, y_0)$ the function $f(x_0, y_0) = (f_1(x_0, y_0), f_2(x_0, y_0))$ given in (10) turns into the form

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t + r(y_0 \cos t - x_0 \sin t) - r(y_0 \cos t - \\ &\quad x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2) dt \\ &= -\frac{1}{4} \pi r x_0 (-4 + x_0^2 + y_0^2), \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t + r(y_0 \cos t - x_0 \sin t) - r(y_0 \cos t - \\ &\quad x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2) dt \\ &= \frac{1}{4} (4d - r y_0 (-4 + x_0^2 + y_0^2)). \end{aligned}$$

The zeros of functions f_1 and f_2 are a pair of conjugate complex vectors and a real pair (x_0^0, y_0^0) satisfying $x_0^0 = 0$ and

$$y_0^0 = \frac{2}{3} \frac{(36r)^{1/3}}{(9d + \sqrt{81d^2 - 48r^2})^{1/3}} + \frac{1}{3} \left(\frac{6}{r}\right)^{1/3} (9d + \sqrt{81d^2 - 48r^2})^{1/3}.$$

Note that y_0^0 is real because $81d^2 > 48r^2 > 0$ by assumption. We observe that the expression of $y_0^0 = y_0^0(r, d)$ does not change when we go back through the rescaling (5) taking $r = \varepsilon^{-1} \rho$ and $d = \varepsilon^{-1} \delta$ according to the hypotheses of Theorem 1.

Moreover we denote $\Gamma = (9d + \sqrt{81d^2 - 48r^2})^{1/3}$ and observe that the matrix $M = (m_{ij}) = \partial(f_1, f_2)/\partial(x_0, y_0)$ at (x_0^0, y_0^0) is diagonal and its elements are $m_{11} = -\pi r \Gamma_+/36$ and $m_{22} = \pi r \Gamma_-$, where

$$\Gamma_{\pm} = -12 \pm \frac{6^{1/3} 24 r^{2/3}}{\Gamma^2} \pm \frac{6^{2/3} \Gamma^2}{r^{2/3}}.$$

The determinant Π_0 of M written in a power series of r around $r = 0$ is

$$\Pi_0 = \frac{3}{8} (2\pi^2 d (4d)^{1/3}) r^{2/3} + \frac{(\pi r)^2}{3} + O(r^{7/3}),$$

which is positive for $|r|$ sufficiently small because $d > 0$. So the averaging theory described in section 3 guarantee the existence of a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that $(x(0, \varepsilon), y(0, \varepsilon))$ tends to (x_0^0, y_0^0) when $\varepsilon \rightarrow 0$.

On the other hand the trace Σ_0 of M at (x_0^0, y_0^0) is

$$\Sigma_0 = -2^{2/3}\pi (2d)^{2/3} r^{1/3} - \frac{2\pi r}{3} + O(r^{4/3}).$$

Thus for $|r|$ sufficiently small the trace Σ_0 of M is negative. So the real part of the eigenvalues of the matrix M are both negative and then the periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ is stable for each ε sufficiently small. So Theorem 1 is proved. \square

Proof of Theorem 2: Now we take $n_2 = n_4 = 1$ and consider $n_1, n_3 > 1$. So we are under the hypotheses of Theorem 2. Now, taking $m = 0$ and doing the rescaling (5) the vector field of system (8) writes

$$(y, -x + \varepsilon^{n_1} r y - \varepsilon^{n_1} r x^2 y - \varepsilon a x^3 - \varepsilon^{n_3} \ell x^5 + \varepsilon d \cos t)^T.$$

Thus we have $F_1(t, \mathbf{x}) = (0, -ax^3 + d \cos t)$ and $f(x_0, y_0) = (f_1(x_0, y_0), f_2(x_0, y_0))$ becomes

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t - a(x_0 \cos t + y_0 \sin t)^3) dt \\ &= \frac{3}{4} a \pi y_0 (x_0^2 + y_0^2), \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t - a(x_0 \cos t + y_0 \sin t)^3) dt \\ &= \frac{1}{4} \pi (4d - 3a x_0 (x_0^2 + y_0^2)). \end{aligned}$$

The real zero (x_0^0, y_0^0) of f_1 and f_2 is

$$(x_0^0, y_0^0) = \left(\left(\frac{4d}{3a} \right)^{1/3}, 0 \right).$$

Again the values (x_0^0, y_0^0) does not depends on ε when we go back to the original parameters α and δ through the rescaling (5). Besides the matrix $M = \partial(f_1, f_2)/\partial(x_0, y_0)$ at (x_0^0, y_0^0) now writes

$$M = \frac{1}{\varepsilon} \begin{pmatrix} 0 & ((3/4)\alpha\delta^2)^{1/3}\pi \\ -3((3/4)\alpha\delta^2)^{1/3}\pi & 0 \end{pmatrix},$$

and then the determinant Π_0 of M is

$$\Pi_0 = \frac{3\pi^2}{2\varepsilon^2} \left(\frac{9\alpha^2\delta^4}{2} \right)^{1/3} > 0.$$

Therefore the averaging theory implies the existence of a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that $(x(0, \varepsilon), y(0, \varepsilon))$ tends to (x_0^0, y_0^0) when $\varepsilon \rightarrow 0$. \square

We observe that since the trace Σ_0 of M is zero and the determinant Π_0 is positive, then the real part of the eigenvalues of M are both zero. So we cannot decide about the stability of the periodic solution of Theorem 2. In what follows we see that the same occurs in Theorem 3.

Proof of Theorem 3: We start considering $n_3 = n_4 = 1$, $n_1, n_2 > 1$ and $m = 0$. Therefore we are under the assumptions of Theorem 3. Doing the rescaling (5) the vector field of system (8) becomes

$$(y, -x + \varepsilon^{n_1} r y - \varepsilon^{n_1} r x^2 y - \varepsilon^{n_2} a x^3 - \varepsilon \ell x^5 + \varepsilon d \cos t)^T.$$

So we conclude that $F_1(t, \mathbf{x}) = (0, -\ell x^5 + d \cos t)$ and then we get

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t - \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= \frac{5}{8} \ell \pi y_0 (x_0^2 + y_0^2)^2, \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t - \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= \frac{1}{8} \pi (8d - 5\ell x_0 (x_0^2 + y_0^2)^2). \end{aligned}$$

Now the real zero (x_0^0, y_0^0) of f_1 and f_2 is

$$(x_0^0, y_0^0) = \left(\left(\frac{8d}{5\ell} \right)^{1/5}, 0 \right).$$

We note that as in Theorems 1 and 2 the root (x_0^0, y_0^0) do not depend on ε after we perform rescaling (5). However using (5) the matrix $M = \partial(f_1, f_2)/\partial(x_0, y_0)$ at (x_0^0, y_0^0) is

$$M = \frac{1}{\varepsilon} \begin{pmatrix} 0 & ((5/8)\lambda\delta^4)^{1/5}\pi \\ -5((5/8)\lambda\delta^4)^{1/5}\pi & 0 \end{pmatrix},$$

whose determinant is

$$\Pi_0 = \frac{5\pi^2}{2\varepsilon^2} \left(\frac{25\lambda^2\delta^8}{2} \right)^{1/5} > 0.$$

Then the averaging method states the existence of a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that $(x(0, \varepsilon), y(0, \varepsilon))$ tends to (x_0^0, y_0^0) when $\varepsilon \rightarrow 0$. The stability of this periodic solution is unknown because the trace Σ_0 of M is zero and the determinant $\Pi_0 > 0$ is positive just as in Theorem 2. \square

Proof of Theorem 4: In what follows we assume that $n_1 = m = 1$ and $n_4 = 2$. Now the expression of the vector field of system (8) is

$$(y, -x + \varepsilon r y - \varepsilon^3 r x^2 y - \varepsilon^{n_2+2} a x^3 - \varepsilon^{n_3+4} \ell x^5 + \varepsilon d \cos t)^T,$$

and then $F_1(t, \mathbf{x}) = (0, ry + d \cos t)$. In this case we obtain

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t + r(y_0 \cos t - x_0 \sin t)) dt \\ &= \pi r x_0, \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t + r(y_0 \cos t - x_0 \sin t)) dt \\ &= \pi(d + r y_0). \end{aligned}$$

It is immediate that the only zero (x_0^0, y_0^0) of f_1 and f_2 in this case is $(x_0^0, y_0^0) = (0, d/r)$. So after going back through the rescaling (5) taking $r = \varepsilon^{-1}\rho$ and $d = \varepsilon^{-2}\delta$ we have

$$(x_0^0, y_0^0) = \left(0, -\frac{\delta}{\varepsilon\rho}\right).$$

In addition the matrix $M = \partial(f_1, f_2)/\partial(x_0, y_0)$ at (x_0^0, y_0^0) is diagonal and its elements are both given by $\rho\pi/\varepsilon$. Consequently M has determinant $\Pi_0 = (\rho\pi/\varepsilon)^2 > 0$ and trace $\Sigma_0 = 2\rho\pi/\varepsilon > 0$. Then averaging theory described in section 3 assure the existence of a 2π -periodic solution $(x(t, \varepsilon), y(t, \varepsilon))$ such that $(x(0, \varepsilon), y(0, \varepsilon))$ tends to (x_0^0, y_0^0) when $\varepsilon \rightarrow 0$. Moreover since ρ is positive this periodic solution is unstable. Then Theorem 4 is proved. \square

Proof of Theorem 5: Now we take $m = 0$, $n_2 = n_3 = n_4 = 1$ and $n_1 > 1$. The expression of the vector field of system (8) in this case is

$$(y, -x + \varepsilon^{n_1} r y - \varepsilon^{n_1} r x^2 y - \varepsilon a x^3 - \varepsilon \ell x^5 + \varepsilon d \cos t)^T,$$

and we get $F_1(t, \mathbf{x}) = (0, -ax^3 - \ell x^5 + d \cos t)$. Hence function $f = (f_1, f_2)$ writes

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t - a(x_0 \cos t + y_0 \sin t)^3 - \\ &\quad \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= \frac{1}{8}\pi y_0(x_0^2 + y_0^2)(6a + 5\ell(x_0^2 + y_0^2)), \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t - a(x_0 \cos t + y_0 \sin t)^3 - \\ &\quad \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= \frac{1}{8}\pi(8d - x_0(x_0^2 + y_0^2)(6a + 5\ell(x_0^2 + y_0^2))). \end{aligned}$$

In order to find the zeros of $f(x_0, y_0)$ we compute a Gröbner basis $\{b_k(x_0, y_0), k = 1, 2, 3\}$ in the variables x_0 and y_0 for the set of polynomials $\{\bar{f}_1(x_0, y_0), \bar{f}_2(x_0, y_0)\}$, where $\bar{f}_{1,2} = (8/\pi)f_{1,2}$. Then we look for the zeros of each $b_k, k = 1, 2, 3$. It is a known fact that the zeros of a Gröbner basis of $\{\bar{f}_1(x_0, y_0), \bar{f}_2(x_0, y_0)\}$ are the zeros of \bar{f}_1 and \bar{f}_2 , and consequently zeros

of f_1 and f_2 too. For more information about a Gröbner basis see [1] and [15].

The Gröbner is

$$\begin{aligned} b_1(x_0, y_0) &= dy_0, \\ b_2(x_0, y_0) &= (6ax_0^2 + 5\ell x_0^4)y_0 + (6a + 10\ell x_0^2)y_0^3 + 5\ell y_0^5, \\ b_3(x_0, y_0) &= -8d + 6ax_0^3 + 5\ell x_0^5 + (6ax_0 + 10\ell x_0^3)y_0^2 + 5\ell x_0 y_0^4. \end{aligned}$$

The only zero of $b_1(x_0, y_0)$ is $y_0^0 = 0$ since $d = \varepsilon^{-1}\delta > 0$. So replacing y_0^0 into $b_3(x_0, y_0)$ and simplifying the new expressions we reduce our problem to find a zero of the polynomial

$$(11) \quad p(x_0) = \frac{1}{5\ell}b_3(x_0, 0) = -\frac{8d}{r\ell} + \frac{6a}{5\ell}x_0^3 + x_0^5.$$

As we know from algebra there is no general formula to provide the roots of a quintic polynomial as polynomial (11). Nevertheless some techniques may become this task easier. An elegant one can be found in [29]. In this paper it is provide a way to study the number of roots (complex and real, including multiplicity) of a polynomial of any order only performing some calculations on the coefficients of the considered polynomial. We will present a brief summary of the algorithmic of this method in the Appendix A at the end of this paper.

By the Fundamental Theorem of Algebra polynomial (11) has 5 roots taking into account their multiplicities and once we want to apply the averaging theory we are only interested in the real simple roots of polynomial (11). Indeed, applying the method due to [29] and summarized in Appendix A we obtain

$$\begin{aligned} D_4 &= \frac{384ad^2}{\ell^3}, \\ D_5 &= \frac{53747712}{78125} \frac{a^5 d^2}{\ell^7} + 20480 \frac{d^4}{\ell^4}. \end{aligned}$$

Therefore as described in Appendix A, since $\alpha\lambda = \varepsilon^2 a\ell < 0$ by hypothesis we have that D_4 is negative. So polynomial (11) has a unique simple real root if $D_5 = D = 0$ according to statement (5) of Appendix A. On the other hand statement (3) says that polynomial (11) has three simple real roots if $D_5 = D < 0$. Moreover D and D_4 does not change when we replace (a, ℓ, d) by $(\varepsilon^{-1}\alpha, \varepsilon^{-1}\lambda, \varepsilon^{-1}\delta)$ using rescaling (5).

Now using the property on zeros of the Gröbner basis cited previously the function $f(x_0, y_0)$ has a zero $(x_0^0, 0)$ if $D = 0$ and three zeros $(x_0^i, 0)$ if $D < 0$, with $i = 1, 2, 3$. Besides the matrix $M = \partial(f_1, f_2)/\partial(x_0, y_0)$ evaluated at $y_0^0 = 0$ after rescaling (5) is

$$M = \frac{1}{\varepsilon} \begin{pmatrix} 0 & \frac{\pi}{8}(6\alpha x_0^2 + 5\lambda x_0^4) \\ -\frac{\pi}{8}(18\alpha x_0^2 + 25\lambda x_0^4) & 0 \end{pmatrix},$$

whose determinant is

$$\Pi(x_0) = \frac{1}{\varepsilon^2} \left(\frac{27}{16} (\alpha \pi x_0^2)^2 + \frac{15}{4} \alpha \lambda (\pi x_0^3)^2 + \frac{125}{64} (\lambda \pi x_0^4)^2 \right).$$

Thus by computing a Gröbner basis for polynomials $\{\Pi(x_0), f_1(x_0, 0), f_2(x_0, 0)\}$ in the variables α, δ, λ and x_0 we get the polynomials $\bar{b}_1(\alpha, \delta, \lambda, x_0) = \delta$ and $\bar{b}_2(\alpha, \delta, \lambda, x_0) = 6\alpha + 5\lambda x_0^2$. So $\bar{b}_1(\alpha, \delta, \lambda, x_0) > 0$ because $\delta > 0$ and it means that we cannot have f_1, f_2 and Π equal to zero simultaneously. Consequently $\Pi(x_0^i) \neq 0$ for all $i = 0, 1, 2, 3$. Then using the averaging theory we conclude the existence of a 2π -periodic solution if $D = 0$ and three 2π -periodic solution if $D < 0$.

Now we exhibit values of α, λ and δ for which system (4) has one or three 2π -periodic solutions. Despite, if consider $a = 25/18, \ell = -1$ and $d = 5/12$ we obtain $a\ell = -25/18 < 0$ and $D = 0$. On the other hand, taking $d = 18a/31$ and $\ell = -42a/155$ we get $a\ell = -42a^2/155 < 0$ and $D = -1425339825408/823543 < 0$. So Theorem 5 is proved. \square

We note that by assumption in Theorem 5 we have $a\ell < 0$. So considering the notation of Appendix A the coefficients $D_2 = -6a/5\ell$ and $D_3 = 384ad^2/\ell^3$ corresponding to polynomial (11) are positive and D_4 is negative. Thus the only possible configurations of roots of the polynomial (11) are those one listed in statements (3) and (5) of the Appendix. This fact means that we cannot have 2 or 5 periodic solutions when we consider $m = 0, n_2 = n_3 = n_4 = 1$ and $n_1 > 1$.

Proof of Theorem 6: We start fixing the values $m = 0, n_1 = n_2 = n_4 = 1$ and $n_3 > 1$. Now the vector field of system (8) writes

$$(y, -x + \varepsilon r y - \varepsilon r x^2 y - \varepsilon a x^3 - \varepsilon^{n_3} \ell x^5 + \varepsilon d \cos t)^T,$$

and then $F_1(t, \mathbf{x}) = (0, r y - r x^2 y - a x^3 + d \cos t)$. With this expression of F_1 function (10) is

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t + r(y_0 \cos t - x_0 \sin t) \\ &\quad - r(y_0 \cos t - x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2 \\ &\quad - a(x_0 \cos t + y_0 \sin t)^3) dt \\ &= -\frac{1}{4}\pi(r x_0(-4 + x_0^2 + y_0^2) - 3a y_0(x_0^2 + y_0^2)), \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t + r(y_0 \cos t - x_0 \sin t) \\ &\quad - r(y_0 \cos t - x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2 \\ &\quad - a(x_0 \cos t + y_0 \sin t)^3) dt \\ &= \frac{1}{4}\pi(4d - r y_0(-4 + x_0^2 + y_0^2) - 3a x_0(x_0^2 + y_0^2)). \end{aligned}$$

In order to find zeros (x_0^*, y_0^*) of $f(x_0, y_0)$ as before we compute a Gröbner basis $\{b_k(x_0, y_0), k = 1, \dots, 14\}$ in the variables x_0 and y_0 now for the set of polynomials $\{\bar{f}_1(x_0, y_0), \bar{f}_2(x_0, y_0)\}$ with $\bar{f}_{1,2} = \mp(4/\pi)f_{1,2}$. We will look for zeros of two elements of the Gröbner basis for the polynomials $\{\bar{f}_1(x_0, y_0), \bar{f}_2(x_0, y_0)\}$ in the variables x_0 and y_0 . These polynomials are

$$\begin{aligned} b_1(x_0, y_0) &= 144a^2dr^3 - 4d^3r^3 + (108a^2d^2r^2 + 144a^2r^4 - 4d^2r^4)y_0 + \\ &\quad 144a^2dr^3y_0^2 + (81a^4d^2 + 18a^2d^2r^2 + d^2r^4)y_0^3, \\ b_2(x_0, y_0) &= 216a^3dr^2 + (-324a^4r^2 - 9a^2d^2r^2 + 36a^2r^4 - d^2r^4)x_0 + \\ &\quad (27a^3d^2r + 216a^3r^3 + 3ad^2r^3)y_0 + (243a^5d + 54a^3dr^2 + \\ &\quad 3adr^4)y_0^2. \end{aligned}$$

We must observe that $b_1(x_0, y_0)$ depends only on y_0 . Then for each zero y_0^* of $b_1(y_0)$ the second polynomial $b_2(x_0, y_0)$ provides a zero x_0^* associated to y_0^* because the coefficient of x_0 in $b_2(x_0, y_0)$ is not zero by hypothesis. Now we will look for zeros of $b_1(y_0)$. Indeed the discriminant Δ of the cubic polynomial $b_1(y_0)$ writes

$$\begin{aligned} \Delta &= -16d^2r^6 (324a^4 + d^2r^2 + 9a^2(d^2 - 4r^2))^2 (2187a^4d^4 + 27d^4r^4 - \\ &\quad 16d^2r^6 + 18a^2(27d^4r^2 - 72d^2r^4 + 32r^6)) \\ &= -16d^2r^6\Delta_1^2\Delta_2. \end{aligned}$$

So if Δ_1 or Δ_2 is zero then Δ is zero and consequently $b_1(y_0)$ has a simple real root y_0^0 because this polynomial has no root with multiplicity 3. Actually $b_1'''(y_0) = 6(81a^4d^2 + 18a^2d^2r^2 + d^2r^4) > 0$. The same occurs if $\Delta_2 > 0$ since this condition implies $\Delta < 0$. On the other hand, if $\Delta_2 < 0$ then $\Delta > 0$ and consequently polynomial $b_1(y_0)$ has three simple real roots y_0^i , $i = 1, 2, 3$. Additionally, replacing each value y_0^i into $b_2(x_0, y_0)$ we obtain the respective values x_0^i , for $i = 0, 1, 2, 3$. We note that coming back through the rescaling (5) the signs of Δ , Δ_1 and Δ_2 does not change because each monomial composing Δ has the same degree.

Now we will verify the condition $M = \det((\partial f / \partial \mathbf{z})(x_0^i, y_0^i)) \neq 0$ for $i = 0, 1, 2, 3$. In fact M is

$$\frac{-\pi}{4\varepsilon} \begin{pmatrix} -6\alpha x_0 y_0 + \rho(-4 + 3x_0^2 + y_0^2) & 2\rho x_0 y_0 - 3\alpha(x_0^2 + 3y_0^2) \\ 2\rho x_0 y_0 + 3\alpha(3x_0^2 + y_0^2) & 6\alpha x_0 y_0 + \rho(-4 + x_0^2 + 3y_0^2) \end{pmatrix},$$

whose determinant Π now is

$$\Pi(x_0, y_0) = \frac{\pi^2}{16\varepsilon^2} \left(27\alpha^2(x_0^2 + y_0^2)^2 + \rho^2(-4 + x_0^2 + y_0^2)(-4 + 3x_0^2 + 3y_0^2) \right).$$

However for each $i = 0, 1, 2, 3$ the determinant $\Pi(x_0^i, y_0^i) \neq 0$ by hypothesis. Therefore using averaging theory described in section 3 system (4) has a 2π -periodic solution if $\Delta_1\Delta_2 = 0$ or $\Delta_2 > 0$ and three 2π -periodic solution if $\Delta_2 < 0$.

Now we present concrete values of α , ρ and δ for which we have one or three periodic solutions. Indeed taking $a = r = 1$ and $d = 6$ we have $\Delta_2 = 3452544 > 0$. Meantime if we consider $d = 6a$ and

$$r = -\frac{9a}{\sqrt{-9 + 4\sqrt{6}}},$$

we obtain $\Delta_2 = -34012224a^8/(9 - 4\sqrt{6})^2 < 0$. We also observe that the values $(r, a, d) = ((555/4)\sqrt{\frac{154073}{9622}}, 185, 22)$ and $(r, a, d) = (585\sqrt{3}, 195, 585\sqrt{2})$ make Δ_1 and Δ_2 equal to zero, respectively. This ends the proof of Theorem 6. \square

Proof of Theorem 7: For this case we assume $m = 0$ and $n_i = 1$, $i = 1, 2, 3, 4$. Then the vector field of system (8) writes

$$(y, -x + \varepsilon ry - \varepsilon rx^2y - \varepsilon ax^3 - \varepsilon \ell x^5 + \varepsilon d \cos t)^T,$$

and we have $F_1(t, \mathbf{x}) = (0, ry - rx^2y - ax^3 - \ell x^5 + d \cos t)$. So it follows that

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t + r(y_0 \cos t - x_0 \sin t) - r(y_0 \cos t - \\ &\quad x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2 - a(x_0 \cos t + y_0 \sin t)^3 - \\ &\quad - \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= -\frac{1}{8}\pi(2rx_0(-4 + x_0^2 + y_0^2) - y_0(x_0^2 + y_0^2)(6a + 5\ell(x_0^2 + y_0^2))), \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t + r(y_0 \cos t - x_0 \sin t) - r(y_0 \cos t - \\ &\quad x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2 - a(x_0 \cos t + y_0 \sin t)^3 - \\ &\quad - \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= \frac{1}{8}\pi(8d + 8ry_0 - (x_0^2 + y_0^2)(6ax_0 + 2ry_0 + 5\ell x_0(x_0^2 + y_0^2))). \end{aligned}$$

We will find zeros of $f(x_0, y_0)$ through the zeros of a Gröbner basis $\{b_k(x_0, y_0)\}$ of it. As before instead of $f(x_0, y_0)$ the Gröbner basis will be related with the functions $\bar{f}_{1,2} = \mp(8/\pi)f_{1,2}$.

One of the elements of the Gröbner basis in the variables x_0 and y_0 is

$$\begin{aligned} b_1(x_0, y_0) &= 144a^2dr^5 - 4d^3r^5 + 960ad\ell r^5 + 1600d\ell^2r^5 + (108a^2d^2r^4 + \\ &\quad 960ad^2\ell r^4 + 2000d^2\ell^2r^4 + 144a^2r^6 - 4d^2r^6 + 960a\ell r^6 + \\ &\quad 1600\ell^2r^6)y_0 + (120ad^3\ell r^3 + 500d^3\ell^2r^3 + 144a^2dr^5 + 1200 \\ &\quad ad\ell r^5 + 2400d\ell^2r^5)y_0^2 + 81a^4d^2r^2 + 540a^3d^2\ell r^2 + 900a^2d^2\ell^2 \\ &\quad r^2 + 18a^2d^2r^4 + 300ad^2\ell r^4 + 900d^2\ell^2r^4 + d^2r^6)y_0^3 + (-450 \\ &\quad a^2d^3\ell^2r - 1500ad^3\ell^3r + 50d^3\ell^2r^3)y_0^4 + 625d^4\ell^4y_0^5. \end{aligned}$$

We note that again $b_1(x_0, y_0)$ depends only on y_0 . Moreover, the Gröbner basis has other element $b_2(x_0, y_0)$ which is linear on x_0 and the coefficients depend on y_0 , where the coefficient C of x_0 is not zero by hypotheses. Its expression is too large and we will omit it here. It can be easily obtained by an algebraic manipulator. So for each zero y_0^* of $b_1(y_0)$ the second polynomial $b_2(x_0, y_0)$ provides a zero x_0^* associated to y_0^* .

Now we will look for zeros of $b_1(y_0)$. Indeed using again Appendix A the conditions on a, r, d and ℓ that provide three zeros, (x_0^i, y_0^i) , where $i = 1, 2, 3$ for $b_1(y_0)$ are $D_5 = -D_5^1 D_5^2 D_5^3 < 0$, where D is given in Theorem 7 and D_5^1 and D_5^2 are the values

$$D_5^1 = \frac{110075314176a^8 r^{20}}{d^{20}(-9a^2 + r^2)^{28}},$$

$$D_5^2 = (59049a^{10}d^4 + 16r^{14} + 36a^2r^{10}(11d^2 - 4r^2) - 81a^4r^6(d^4 - 12d^2r^2 + 16r^4) - 6561a^8(3d^4r^2 - 4d^2r^4) + 729a^6(3d^4r^4 - 28d^2r^6 + 16r^8))^2.$$

By hypothesis $ar = \varepsilon^{-2}\alpha\rho \neq 0$ and $D_5^2 \neq 0$, then D_5^1 and D_5^2 are positive. Therefore, in order to have D_5 negative we must have D positive. On the other hand, if D_5 is positive then according to statement (2) of Appendix A we have a unique zero (x_0^0, y_0^0) for $b_1(y_0)$ because the value

$$D_2 = -\frac{1296a^2r^4(-3a^2 + r^2)^2}{d^2(-9a^2 + r^2)^4},$$

is negative if $(r^2 - 3a^2)(r^2 - 9a^2) \neq 0$. In addition by considering $a = \varepsilon^{-1}\alpha$, $r = \varepsilon^{-1}\rho$ and $d = \varepsilon^{-1}\delta$ we get

$$M = \frac{-\pi}{8\varepsilon} \begin{pmatrix} 2\rho(-4 + 3x_0^2 + y_0^2) - \Gamma_1 & \Gamma_2 - \Gamma_4 - 5\lambda\Gamma_3(x_0^2 + 5y_0^2) \\ \Gamma_2 + \Gamma_4 + 5\lambda\Gamma_3(5x_0^2 + y_0^2) & 2\rho(-4 + x_0^2 + 3y_0^2) - \Gamma_1 \end{pmatrix}$$

where $\Gamma_1 = 2x_0y_0(3\alpha + 5\ell(x_0^2 + y_0^2))$, $\Gamma_2 = -4\rho x_0y_0$, $\Gamma_3 = x_0^2 + y_0^2$ and $\Gamma_4 = 6\alpha(x_0^2 + 3y_0^2)$. Moreover the determinant Π of M writes

$$\Pi(x_0, y_0) = \frac{1}{\varepsilon^2} (4\rho^2(-4 + x_0^2 + y_0^2)(-4 + 3x_0^2 + 3y_0^2) + (x_0^2 + y_0^2)^2(6\alpha + \rho\lambda(x_0^2 + y_0^2)(18\alpha + 25\lambda x_0^2 + 3y_0^2))).$$

However, by hypothesis $\Pi(x_0^i, y_0^i) \neq 0$ for $i = 0, 1, 2, 3$ and hence we conclude the first part of Theorem 7.

Now we provide values for α, ρ, λ and δ for which we have one or three 2π -periodic solutions. First we observe that taking $(a, r, d) = (1, 2, 8/3)$ we obtain

$$D = -\frac{2770035802112}{6561} < 0.$$

However if we consider

$$(a, r, d, \ell) = (1/\sqrt{3}, 1, 1, -1/(5\sqrt{3})),$$

then $D = 2752$. So Theorem 7 is proved. \square

Now we will prove that under the conditions $m = 0$ and $n_i = 1$, $i = 1, 2, 3, 4$ and the assumptions of Theorem 7 we cannot have 2 or 5 periodic solutions by using the averaging theory and the rescaling (5). Indeed we observe that the only possibility to have 5 periodic solutions that the statement (1) of Appendix A holds. However this condition does not hold since D_2 is negative for any a , r and d satisfying the hypotheses of Theorem 7.

In addition we note that the only condition that provides two periodic solutions according with Appendix A is statement (7), and it needs $D_5 = D_4 = E_2 = 0$. Nevertheless we start considering this condition and we will find a Gröbner basis for the set of polynomials $\{D_4, D_5, E_2\}$ in the variables a , d and r . First we will consider the factor D_5^2 of D_5 because $D_5^1 \neq 0$ by hypothesis. In this case we obtain 55 polynomials in the Gröbner basis, where the first one is $g(d, r) = r^{62}\bar{g}(d, r)$ and

$$\begin{aligned} \bar{g}(d, r) = & 91125d^{12} - 438800d^{10}r^2 + 919360d^8r^4 - 1038464d^6r^6 + \\ & 660992d^4r^8 - 225280d^2r^{10} + 32768r^{12}. \end{aligned}$$

Since $r \neq 0$ we must find a zero of $\bar{g}(d, r)$. So solving $\bar{g}(d, r) = 0$ in the variable r we obtain 6 pairs of values

$$r_{\pm}^i = \pm d\sqrt{q_0^i},$$

where $i = 1, \dots, 6$ and for each i the value q_0^i is the i th-root of the polynomial

$$\begin{aligned} q(x) = & 91125 - 438800x + 919360x^2 - 1038464x^3 + 660992x^4 \\ & - 225280x^5 + 32768x^6. \end{aligned}$$

This polynomial has only complex roots. Indeed, if we study the function $q'(x)$ which is given by

$$\begin{aligned} q'(x) = & -438800 + 1838720x - 3115392x^2 + 2643968x^3 - 1126400x^4 \\ & + 196608x^5, \end{aligned}$$

we can apply the method described in Appendix A to show that the respective values D_2 and D_5 related to $q'(x)$ are negative and positive, respectively. Therefore $q'(x)$ has only one real root q'_0 whose approximate value is $q'_0 = 106703/100000$. Additionally the approximate value of $q(x)$ evaluated in q'_0 is $q(q'_0) = 16558687/10000 > 0$. So if we observe that the coefficient of x^6 is positive it follows that the minimum value of $q(x)$ is positive. Then each r_{\pm}^i , $i = 1, \dots, 6$ is a complex value and the correspondent Gröbner basis has no zeros. Then we cannot have a common real zero of D_4 , D_5^2 and E_2 and so statement (7) in Appendix A does not hold. Consequently it is not possible to obtain 2 periodic solutions. The proof considering the factor D of D_5 instead of D_5^2 leads to the same polynomial $g(d, r)$ and then we have the same conclusion.

Proof of Theorem 8: In what follows we take $m = 0$, $n_1 = n_3 = n_4 = 1$ and $n_2 > 1$. So the vector field of system (8) becomes

$$(y, -x + \varepsilon ry - \varepsilon r x^2 y - \varepsilon^{n_2} a x^3 - \varepsilon \ell x^5 + \varepsilon d \cos t)^T.$$

and we obtain $F_1(t, \mathbf{x}) = (0, ry - rx^2y - \ell x^5 + d \cos t)$. So $f(x_0, y_0)$ writes

$$\begin{aligned} f_1(x_0, y_0) &= \int_0^{2\pi} -(\sin t)(d \cos t + r(y_0 \cos t - x_0 \sin t) - r(y_0 \cos t - \\ &\quad x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2 - \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= -\frac{1}{8}\pi(2rx_0(-4 + x_0^2 + y_0^2) - 5\ell y_0(x_0^2 + y_0^2)^2), \\ f_2(x_0, y_0) &= \int_0^{2\pi} (\cos t)(d \cos t + r(y_0 \cos t - x_0 \sin t) - r(y_0 \cos t - \\ &\quad x_0 \sin t)(x_0 \cos t + y_0 \sin t)^2 - \ell(x_0 \cos t + y_0 \sin t)^5) dt \\ &= \frac{1}{8}\pi(8d - 2ry_0(-4 + x_0^2 + y_0^2) - 5\ell x_0(x_0^2 + y_0^2)^2). \end{aligned}$$

Again we will find zeros of $f(x_0, y_0)$ through the roots of a Gröbner basis $\{b_k(x_0, y_0)\}$ of $f(x_0, y_0)$. We will find a Gröbner basis of the functions $\bar{f}_{1,2} = \mp(8/\pi)f_{1,2}$.

An element of the Gröbner basis in the variables x_0 and y_0 is

$$\begin{aligned} b_1(x_0, y_0) &= -4d^3r^5 + 1600dL^2r^5 + (2000d^2\ell^2r^4 - 4d^2r^6 + 1600L^2R^6)y_0 \\ &\quad + (500d^3\ell^2r^3 + 2400d\ell^2r^5)y_0^2 + (900d^2\ell^2r^4 + d^2r^6)y_0^3 + \\ &\quad 50d^3\ell^2r^3y_0^4 + 625d^4\ell^4y_0^5. \end{aligned}$$

As before $b_1(x_0, y_0)$ depends only on y_0 and another element $b_2(x_0, y_0)$ of the Gröbner basis is linear on x_0 with coefficients depending on y_0 , where the coefficient C of x_0 in $b_2(x_0, y_0)$ is not zero by hypotheses. We will not present the expression of $b_2(x_0, y_0)$ in order to avoid large expressions. Then for each zero y_0^* of $b_1(y_0)$ we have a second zero x_0^* through $b_2(x_0, y_0)$ related to y_0^* .

In order to apply the method described in [29] and Appendix A for $b_1(y_0)$ we will perform the translation $y_0 = \varphi - (2r^3/d(125\ell)^2)$. With this translation we obtain a new polynomial b_1^* into the form

$$b_1^*(\varphi) = \varphi^5 + \frac{4500\ell^2r^4 - 3r^6}{3125d^2\ell^4}\varphi^3 + \frac{2k_1}{k_1d^3\ell^6}\varphi^2 + \frac{4r^4k_2}{k_2d^4\ell^8}\varphi - \frac{4r^5k_3}{k_3d^5\ell^{10}},$$

where

$$\begin{aligned} k_1 &= 156250d^2\ell^4r^3 + 750000\ell^4r^5 - 13500\ell^2r^7 + r^9, \\ \overline{k_1} &= 390625, \\ k_2 &= 39062500d^2\ell^6 - 390625\ell^4(d^2 - 80\ell^2)r^2 - 1500000\ell^4r^4 + 13500\ell^2r^6 + \\ &\quad 3r^8, \\ \overline{k_2} &= 48828125, \\ k_3 &= 48828125d^4\ell^6 - 781250d^2(25000\ell^8 - 500\ell^6r^2 + 3\ell^4r^4) + 2r^4 \\ &\quad (156250000\ell^6 - 3750000\ell^4r^2 + 22500\ell^2r^4 + 9r^6), \\ \overline{k_3} &= 30517578125. \end{aligned}$$

We observe that the translation performed do not change the number or kind of the zeros of the original polynomial b_1 . Now we will apply the method of Appendix A for b_1^* . Indeed we have

$$\begin{aligned} D_2 &= N_2, \\ D_3 &= -\frac{48r^6}{9765625d^6\ell^{10}}N_3, \\ D_4 &= -\frac{16r^{12}}{3814697265625d^{12}\ell^{18}}N_4, \\ D_5 &= \frac{256r^{20}}{1490116119384765625d^{20}\ell^{26}}N_5M_5. \end{aligned}$$

Therefore if D_5 is negative then b_1^* and consequently b_1 has exactly three zeros and hence function $f = (f_1, f_2)$ has exactly three zeros (x_0^i, y_0^i) , $i = 1, 2, 3$. On the other hand if D_5 is positive and one of the values D_2, D_3 or D_4 is non-positive, then f has exactly one zero (x_0^0, y_0^0) . Moreover using the rescaling (5) the matrix M is the same than the one of the proof of Theorem 7 taking $a = 0$. In addition the determinant Π of M writes

$$\Pi(x_0, y_0) = \frac{1}{\varepsilon^2} (125\lambda^2 (x_0^2 + y_0^4) + 4\rho^2(-4 + x_0^2 + y_0^2)(-4 + 3x_0^2 + 3y_0^2)).$$

By hypothesis $\Pi(x_0^i, y_0^i) \neq 0$ for $i = 0, 1, 2, 3$, then we have the first part of Theorem 8 proved.

Now we exhibit values of ρ , λ and δ for which we have either one, or three periodic solutions. Firstly we consider

$$(r, \ell, d) = \left(\sqrt{31}, 1, \frac{1}{125} \sqrt{1547875 - 226851\sqrt{35}} \right).$$

With these values we obtain

$$\begin{aligned} N_3 &= \frac{1}{625} (206837701817900 - 10419995302263\sqrt{35}), \\ N_5 &= \frac{2(-649491478051728715458244 + 109639832554794027558525\sqrt{35})}{48828125}, \end{aligned}$$

which are positive. On the other hand, considering $(r, \ell, d) = (\sqrt{31}/4, 1, 1)$ we get $N_5 = -258261575 / 1048576 < 0$. This ends the proof of Theorem 8. \square

Now we will show that if $m = 0$, $n_1 = n_3 = n_4 = 1$ and $n_2 > 1$, then we cannot have 2 periodic solutions by using averaging theory described in section 3 and rescaling (5). Indeed in order that the function $b_1^*(\varphi)$, given in the proof of Theorem 8, has two periodic solutions we need statement (7) of Appendix A. We start considering the conditions $N_5 = N_4 = E_2 = 0$ and we will see that these equalities implies that N_3 cannot be negative. We claim that N_5 and M_5 are factors of D_5 as we saw in the last proof. Also we will not present the expression of E_2 in order to avoid its large expression. It can be obtained by an algebraic manipulator as Mathematica. Additionally we note that $N_4 = N_5 = 0$ implies $D_4 = D_5 = 0$, which are necessary conditions for having exactly 2 real roots.

We start replacing the condition $N_4 = N_5 = E_2 = 0$ for other ones easier when $r > 0$. It is easy to see that if $r = 0$ we have $N_3 = 0$ and consequently we cannot get 2 roots for b_1^* . Now we obtain a Gröbner basis for the set of polynomials $\{N_4, N_5, E_2\}$ in the variables d , r and ℓ . This basis has twelve elements, where two of them are

$$\begin{aligned} g_1(r, \ell) &= 125 \cdot 10^8 \ell^8 + 2 \cdot 10^8 \ell^6 r^2 - 100000 \ell^4 r^4 - 10400 \ell^2 r^6 - 3r^8, \\ g_2(d, r, \ell) &= 25d^4 \ell^2 - 110000d^2 \ell^4 - 4000000 \ell^6 - 1400d^2 \ell^2 r^2 + 80000 \ell^4 r^2 - \\ &\quad 3d^2 r^4 + 1200 \ell^2 r^4. \end{aligned}$$

In addition the resultant of these two polynomials with respect to the variable r has the factor

$$g_3(d, \ell) = d^8 - 1240000d^6 \ell^2 - 269440000d^4 \ell^4 + 6144 \cdot 10^6 d^2 \ell^6 + 28672 \cdot 10^8 \ell^8.$$

Consequently we will replace the problem of finding a zero of N_4 , N_5 and E_2 by the problem of finding a zero of g_1 , g_2 and g_3 . Moreover we suppose that we have a common zero between each g_i and N_3 , $i = 1, 2, 3$. With this supposition and computing the resultant between g_1 and N_3 we obtain a new polynomial g_4 in the variables r and d given by

$$\begin{aligned} g_4(r, d) &= 1423828125d^{16} + 25974000000d^{14}r^2 - 4793338800000d^{12}r^4 - \\ &\quad 478810245120000d^{10}r^6 + 1711832243200000d^8r^8 - \\ &\quad 125591060860108800d^6r^{10} - 1334616713986048000d^4r^{12} + \\ &\quad 5191865574606503936d^2r^{14} - 4405603330689073152r^{16}. \end{aligned}$$

However the resultant between g_3 and g_4 writes Kr^{128} , where K is a positive constant. This polynomial cannot be zero since $r \geq 0$. It means that when we consider each g_i zero, N_3 must be positive or negative, exclusively. But taking the values $(r, \ell, d) = (r_0, \ell_0, 1)$ we have $g_i \equiv 0$, for each $i = 1, 2, 3$ and N_3 is approximately $8738483/2500 > 0$, where r_0 and ℓ_0 are roots of the

polynomials

$$\bar{r}(x) = -125 - 44400x^2 + 184640x^4 - 237568x^6 + 86016x^8,$$

and

$$\bar{l}(x) = 1 - 1240000x^2 - 269440000x^4 + 6144000000x^6 + 2867200000000x^8.$$

respectively. So N_3 is positive when $g_i \equiv 0$, for each $i = 1, 2, 3$ and then D_3 is negative. Hence using the factor N_5 of D_5 we cannot obtain 2 periodic solutions. The proof that cannot exist 2 periodic solutions for the case that we consider the factor M_5 of D_5 instead of N_5 is similar and we will omit it here.

We remark that we cannot prove analytically the non-existence of 5 periodic solutions for system (8) considering $m = 0$, $n_1 = n_3 = n_4 = 1$ and $n_2 > 1$. Actually, using the algebraic manipulator Mathematica we obtained evidences that this number of periodic solutions cannot happen, but an analytical treatment is not trivial.

2.2. Discussion of the results. Now we discuss some aspects of the averaging method presented in section 3 in order to find periodic solutions in system (4). In fact by using the averaging theory and the rescaling (5) we shall see that we cannot prove that system (4) has periodic solutions except in the cases presented in Theorems from 1 to 8.

We start studying the possible values to the powers of ε in system (8). This is important because these powers play an important role in averaging theory described in section 3 because they determine the terms of order 1 that we are interested in. Indeed we note that each one of the 5 different powers of ε in system (8) must be non-negative. Therefore considering these powers as zero or positive we have 32 possible combinations of these 5 different powers of ε . Actually some of them are not algebraically possible. Table 1 exhibit only the possible case.

Observing Table 1 we see that in fact we have only 18 cases. Moreover in order to apply averaging theory, for which one of the 18 cases we must integrate the equations of the non-perturbed part of vector field of system (8). This is not a simple task because the major part of these equations are nonlinear and non-autonomous. Indeed in each case from 1 to 8 and from 11 to 16 we could not integrate the equations even using the algebraic manipulators Mathematica or Maple. The non-integrable cases from Table 1 are listed above.

$$\text{Caso 1: } F_0(t, x) = (y, -x + ry - ax^3 - rx^2y - lx^5 + d \cos t),$$

$$\text{Caso 2: } F_0(t, x) = (y, -x + ry - ax^3 - rx^2y - lx^5),$$

$$\text{Caso 3: } F_0(t, x) = (y, -x + ry - ax^3 - rx^2y + d \cos t),$$

$$\text{Caso 4: } F_0(t, x) = (y, -x + ry - ax^3 - rx^2y),$$

$$\text{Caso 5: } F_0(t, x) = (y, -x + ry - rx^2y - lx^5 + d \cos t),$$

$$\text{Caso 6: } F_0(t, x) = (y, -x + ry - rx^2y - lx^5),$$

$$\text{Caso 7: } F_0(t, x) = (y, -x + ry - rx^2y + d \cos t),$$

Possible combination of powers of ε for the system (9)					
$n_1 = 0$	$2m + n_1 = 0$	$2m + n_2 = 0$	$4m + n_3 = 0$	$-m + n_4 = 0$	C1
				$-m + n_4 > 0$	C2
			$4m + n_3 > 0$	$-m + n_4 = 0$	C3
				$-m + n_4 > 0$	C4
		$2m + n_2 > 0$	$4m + n_3 = 0$	$-m + n_4 = 0$	C5
				$-m + n_4 > 0$	C6
			$4m + n_3 > 0$	$-m + n_4 = 0$	C7
				$-m + n_4 > 0$	C8
	$2m + n_1 > 0$	$2m + n_2 = 0$	\emptyset		
			$2m + n_2 > 0$	$4m + n_3 = 0$	\emptyset
$4m + n_3 > 0$		$-m + n_4 = 0$		C9	
		$-m + n_4 > 0$	C10		
$n_1 > 0$	$2m + n_1 = 0$	\emptyset			
	$2m + n_1 > 0$	$2m + n_2 = 0$	$4m + n_3 = 0$	$-m + n_4 = 0$	C11
				$-m + n_4 > 0$	C12
			$4m + n_3 > 0$	$-m + n_4 = 0$	C13
				$-m + n_4 > 0$	C14
		$2m + n_2 > 0$	$4m + n_3 = 0$	$-m + n_4 = 0$	C15
				$-m + n_4 > 0$	C16
			$4m + n_3 > 0$	$-m + n_4 = 0$	C17
				$-m + n_4 > 0$	C18

TABLE 1. Here, when appear \emptyset , this means that the corresponding cases cannot occur. The notation Ci, $i = 1, \dots, 18$ enumerate each possible case.

- Caso 8:* $F_0(t, x) = (y, -x + ry - rx^2y),$
Caso 11: $F_0(t, x) = (y, -x - ax^3 - lx^5 + d \cos t),$
Caso 12: $F_0(t, x) = (y, -x - ax^3 - lx^5),$
Caso 13: $F_0(t, x) = (y, -x - ax^3 + d \cos t),$
Caso 14: $F_0(t, x) = (y, -x - ax^3),$
Caso 15: $F_0(t, x) = (y, -x - lx^5 + d \cos t),$
Caso 16: $F_0(t, x) = (y, -x - lx^5).$

In particular we observe that cases 12, 14 and 16 turn the non-perturbed part of system (8) into a Hamiltonians system. In [4] the authors provide a method to apply averaging theory in planar systems when the system is Hamiltonian but the expressions become also to much complicate and again we could not integrate the equations in cases 12, 14 and 16.

In cases 9, 10 and 17 we can integrate the expressions but in these cases the hypotheses of averaging method do not apply. In these cases we have the following expressions for $F_0(t, \mathbf{x})$.

- Caso 9:* $F_0(t, \mathbf{x}) = (y, -x + ry + d \cos t),$
Caso 10: $F_0(t, \mathbf{x}) = (y, -x + ry),$
Caso 17: $F_0(t, \mathbf{x}) = (y, -x + d \cos t).$

Solution $x(t)$ in case 9 is

$$C^- e^{\frac{1}{2}t(r-\sqrt{-4+r^2})} + C^+ e^{\frac{1}{2}t(r+\sqrt{-4+r^2})} - (d/r) \sin t,$$

where

$$C^\mp = \frac{\mp 2d + r \left((\pm r + \sqrt{-4 + r^2}) x_0 \mp 2y_0 \right)}{2r\sqrt{-4 + r^2}}.$$

In order that $x(t)$ be periodic we must have C^- and C^+ equal to zero. But these conditions are verified only if we take $x_0 = 0$ and $y_0 = -d/r$. So x_0 and y_0 are fixed and then the unperturbed system $\dot{x} = F_0(t, x)$ has no submanifold of periodic solutions. Consequently we can not apply averaging theory in this case.

On the other hand, in case 10 solution $x(t)$ writes

$$C^- e^{\frac{1}{2}t(r-\sqrt{-4+r^2})} + C^+ e^{\frac{1}{2}t(r+\sqrt{-4+r^2})} - (d/r) \sin t,$$

where

$$C^\mp = \frac{(\pm r + \sqrt{-4 + r^2}) x_0 \mp 2y_0}{2r\sqrt{-4 + r^2}}.$$

Again we need to chose C^- and C^+ equal to zero but this happen only if $(x_0, y_0) = (0, 0)$. So we cannot apply averaging theory because $(0, 0)$ is the equilibrium point of the non-perturbed part of system (8) in case 10.

Finally in case 17 solutions $x(t)$ and $y(t)$ have the form

$$\begin{aligned} x(t) &= x_0 \cos t + y_0 \sin t + \frac{d}{2}t \cos t, \\ y(t) &= y_0 \cos t - x_0 \sin t + \frac{d}{2}(t \cos t + \sin t). \end{aligned}$$

It is immediate to note that these solutions are non-periodic because d is positive.

Case 18 provide positive results and Theorems from 1 to 8 are based in this case. In fact we observe that in case 18 the vector field of system (8) is $(y, -x + \varepsilon^{n_1}ry - \varepsilon^{2m+n_1}rx^2y - \varepsilon^{2m+n_2}ax^3 - \varepsilon^{4m+n_3}\ell x^5 + \varepsilon^{-m+n_4}d \cos t)^T$.

As we commented before the periodic solutions of our problem correspond to the simple zeros of function (10). So in order to calculate the zeros of the function $f(\mathbf{z})$ given in (10) we must determine $F_1(t, \mathbf{x})$, where $F_1(t, \mathbf{x})$ is determined by the terms of order 1 on ε of the vector field of system (8). However we see that the expression of $F_1(t, \mathbf{x})$ depends on the values m and n_i , $i = 1, 2, 3, 4$. In fact, if m is positive and observing the conditions (7) the only terms of the vector field of order 1 on ε can be generate by powers n_1 and $-m + n_4$, where these two values can be 1 or greater than 1. This implies four possibilities. On the other hand, if m is zero the powers of ε in the vector field of system (8) depend on n_1, n_2, n_3 and n_4 . Again, each one of these powers can be 1 or greater than 1. So, if m is zero we have 16 possibilities for F_1 . Then case 18 has 20 subcases corresponding to the different possibilities of $F_1(t, \mathbf{x})$. These subcases are presented in Table 2.

Theorems from 1 to 8 correspond to subcases 8, 10, 11, 17, 5, 3, 1 and 4, respectively. These are the only subcases of case 18 that the averaging method provide positive results. Indeed, in cases 15, 16, 19 and 20 function (10) do not have zeros. On the other hand, in cases 2, 6, 7, 13, 14, 18 the only zero of function (10) is $(x_0, y_0) = (0, 0)$, that correspond to the equilibrium point of the system, and consequently in these subcases the system does not have periodic solutions. In cases 9 and 12 function (10) has real zeros different from $(0, 0)$ but they are non-isolated and then the Jacobian of function (10) at the zero is zero, and consequently the averaging theory cannot be applied.

3. THE AVERAGING THEORY FOR PERIODIC SOLUTIONS

Now we present the basic results on the averaging theory of first order that we need to proving our results.

Consider the problem of bifurcation of T -periodic solutions from differential systems of the form

$$(12) \quad \dot{\mathbf{x}} = F_0(t, \mathbf{x}) + \varepsilon F_1(t, \mathbf{x}) + \varepsilon^2 R(t, \mathbf{x}, \varepsilon),$$

Subc.	Conditions	Second coordinate of $F_1(t, \mathbf{x})$
1	$m = 0, n_i = 1, i = 1, 2, 3, 4$	$ry - ax^3 - rx^2y - \ell x^5 + d \cos t$
2	$m = 0, n_i = 1, i = 1, 2, 3, n_4 > 1$	$ry - ax^3 - rx^2y - \ell x^5$
3	$m = 0, n_i = 1, i = 1, 2, 4, n_3 > 1$	$ry - ax^3 - rx^2y + d \cos t$
4	$m = 0, n_i = 1, i = 1, 3, 4, n_2 > 1$	$ry - rx^2y - \ell x^5 + d \cos t$
5	$m = 0, n_i = 1, i = 2, 3, 4, n_1 > 1$	$-ax^3 - \ell x^5 + d \cos t$
6	$m = 0, n_1 = n_2 = 1, n_3, n_4 > 1$	$ry - ax^3 - rx^2y$
7	$m = 0, n_1 = n_3 = 1, n_2, n_4 > 1$	$ry - rx^2y - \ell x^5$
8	$m = 0, n_1 = n_4 = 1, n_2, n_3 > 1$	$ry - rx^2y + d \cos t$
9	$m = 0, n_2 = n_3 = 1, n_1, n_4 > 1$	$-ax^3 - \ell x^5$
10	$m = 0, n_2 = n_4 = 1, n_1, n_3 > 1$	$-ax^3 + d \cos t$
11	$m = 0, n_3 = n_4 = 1, n_1, n_2 > 1$	$-\ell x^5 + d \cos t$
12	$m = 0, n_1 = 1, n_i > 1, i = 2, 3, 4$	$ry - rx^2y$
13	$m = 0, n_2 = 1, n_i > 1, i = 1, 3, 4$	$-ax^3$
14	$m = 0, n_3 = 1, n_i > 1, i = 1, 2, 4$	$-\ell x^5$
15	$m > 0, n_4 = 1, n_i > 1, i = 1, 2, 3$	$d \cos t$
16	$m > 0, n_i > 1, i = 1, 2, 3, 4$	0
17	$m > 0, n_1 = 1, -m + n_4 = 1$	$ry + d \cos t$
18	$m > 0, n_1 = 1, -m + n_4 > 1$	ry
19	$m > 0, n_1 > 1, -m + n_4 = 1$	$d \cos t$
20	$m > 0, n_1 > 1, -m + n_4 > 1$	0

TABLE 2. Possible expressions for $F_1(t, \mathbf{x})$ when $m^2 + n_2^2$, $m^2 + n_3^2$, $n_4 - m$ and n_1 are positives. We exhibit only the second coordinate of $F_1(t, \mathbf{x})$ because the first one has no terms depending on ε .

with $\varepsilon = 0$ to $\varepsilon \neq 0$ sufficiently small. Here the functions $F_0, F_1 : \mathbb{R} \times \Omega \rightarrow \mathbb{R}^n$ and $R : \mathbb{R} \times \Omega \times (-\varepsilon_f, \varepsilon_f) \rightarrow \mathbb{R}^n$ are \mathcal{C}^2 , T -periodics in the first variable and Ω is an open subset of \mathbb{R}^n . One of the main assumption is that the unperturbed system

$$(13) \quad \dot{\mathbf{x}} = F_0(t, \mathbf{x}),$$

has a manifold of periodic solutions. A solution of this problem is given using averaging theory.

Indeed, assume that there is an open set V with $\bar{V} \subset D \subset \Omega$ and such that for each $\mathbf{z} \in \bar{V}$, $\mathbf{x}(\cdot, \mathbf{z}, 0)$ is T -periodic, where $\mathbf{x}(\cdot, \mathbf{z}, 0)$ is the solution of the unperturbed system (13) with $\mathbf{x}(0) = \mathbf{z}$. As answer to the problem of bifurcation of T -periodic solutions from $\mathbf{x}(\cdot, \mathbf{z}, 0)$ is given in the following Theorem.

Theorem 9. *We assume that there exists an open set V with $\bar{V} \subset D$ and such that for each $\mathbf{z} \in \bar{V}$, $\mathbf{x}(\cdot, \mathbf{z}, 0)$ is T -periodic and consider the function $f : \bar{V} \rightarrow \mathbb{R}^n$ given by*

$$f(\mathbf{z}) = \int_0^T Y^{-1}(t, \mathbf{z}) F_1(t, \mathbf{x}(t, \mathbf{z}, 0)) dt.$$

Then the following statements hold.

- (a) *If there exists $a \in V$ with $f(a) = 0$ and $\det((\partial f / \partial \mathbf{z})(a)) \neq 0$, then there exists a T -periodic solution $\varphi(\cdot, \varepsilon)$ of system (12) such that $\varphi(0, \varepsilon) \rightarrow a$ as $\varepsilon \rightarrow 0$.*
- (b) *The type of stability of the periodic solution $\varphi(\cdot, \varepsilon)$ is given by the eigenvalues of the Jacobian matrix $M = ((\partial f / \partial \mathbf{z})(a))$.*

For a proof of Theorem 9(a) see Corollary 1 of [3].

In fact, the result of Theorem 9 is a classical result due to Malkin [20] and Roseau [21]. For a shorter proof of Theorem 9(a), see [3].

For Additional information on averaging theory see the book [23].

ACKNOWLEDGMENTS

The first author is supported by the FAPESP-BRAZIL grants 2010/18015-6 and 2012/05635-1. The second author is partially supported by the grants MINECO/FEDER MTM 2008-03437, AGAUR 2009SGR 410, ICREA Academia and FP7 PEOPLE-2012-IRSES-316338 and 318999 and CAPES-MECD grant PHB-2009-0025-PC.

REFERENCES

- [1] W. W. ADAMS AND P. LOUSTAUNAU, *An Introduction to Gröbner Bases*, American Mathematical Society, Graduate Studies in Mathematics, Vol. **3**, 1994.
- [2] K. BOLD, C. EDWARDS, J. GUCKENHEIMER, S. GUHARAY, K. HOFFMAN, J. HUBBARD, R. OLIVA AND W. WECKESSER, *The forced Van der Pol equation II: Canards in the reduced system*, SIAM J. Appl. Dyn. Syst. **2** (2003), 570–608.
- [3] A. BUICĂ, J. P. FRANÇOISE AND J. LLIBRE, *Periodic solutions of nonlinear periodic differential systems with a small parameter*, Comm. on Pure and Appl. Anal. **6** (2007), 103–111.
- [4] A. BUICĂ AND J. LLIBRE, *Averaging methods for finding periodic orbits via Brouwer degree*, Bull. Sci. Math. **128** (2004), 7–22.
- [5] A. CHEN AND G. JIANG, *Periodic solution of the Duffing-Van der Pol oscillator by homotopy perturbation method*, Int. J. Comput. Math **87** (2010), 2688–2696.
- [6] Y. CHEN AND J. LIU, *Uniformly valid solution of limit cycle of the Duffing-van der Pol equation*, Mech. Res. Comm. **36** (2009), 845–850.
- [7] W. O. CRIMINALE, T. L. JACKSON AND P. W. NELSON, *Limit cycle-strange attractor competition*, Stud. Appl. Math. **112**, (2004), 133–160.
- [8] C. EGAMI AND N. HIRANO, *Periodic solutions for forced van der Pol type equations*, Mathematical economics **1264**, (2001), 159–172.
- [9] R. D. EUZÉBIO AND J. LLIBRE, *Periodic Solutions of El Niño Model through the Vallis Differential System*, preprint.
- [10] T. H. FAY, *The forced Van der Pol equation*, Int. Journal of Math. Educ. in Sci. and Tech. **40**(5) (2009), 669–677.

- [11] J. GUCKENHEIMER, K. HOFFMAN AND W. WECKESSER, *The forced Van der Pol equation I: The slow flow and its bifurcations*, SIAM J. Appl. Dyn. Syst. **2** (2003), 1–35.
- [12] F. M. M. KAKMENI, S. BOWONG, C. TCHAWOUA AND E. KAPTOUOM, *Strange attractors and chaos control in a Duffing–Van der Pol oscillator with two external periodic forces*, J. Sound Vib. **227**(4–5) (2004), 783–799.
- [13] F. M. M. KAKMENI, S. BOWONG, C. TCHAWOUA AND E. KAPTOUOM, *Chaos control and synchronization of a ϕ^6 -Van der Pol oscillator*, Phys. Lett. A **322**(5–6) (2004), 305–323.
- [14] H. K. LEUNG, *Synchronization dynamics of coupled van der Pol systems*, Physica A. **321** (2003), 248–255.
- [15] H. LI, *Gröbner Bases in Ring Theory*, World Scientific Publishing, 2011.
- [16] Z. LI, W. XU AND X. ZHANG, *Analysis of chaotic behavior in the extended Duffing–Van der Pol system subject to additive non-symmetry biharmonic excitation*, Appl. Math. Comput. **183** (2006), 858–871.
- [17] D. LIU AND H. YAMAURA, *Chaos control of a ϕ^6 -Van der Pol oscillator driven by external excitation*, Nonlinear Dynamics **68**(1–2) (2012), 95–105.
- [18] J. LLIBRE AND C. VIDAL, *Periodic solutions of a periodic FitzHugh–Nagumo differential system*, preprint.
- [19] M. MA, J. ZHOU AND J. CAI, *Practical synchronization of second-order non-autonomous systems with parameter mismatch and its applications*, Nonlinear Dyn. **69** (2012), 1285–1292.
- [20] I. G. MALKIN, *Some problems of the theory of nonlinear oscillations*, (Russian) Gosudarstv. Izdat. Tehn.-Teor. Lit., Moscow, 1956.
- [21] M. ROSEAU, *Vibrations non linéaires et théorie de la stabilité*, (French) Springer Tracts in Natural Philosophy, Vol. 8 Springer–Verlag, Berlin–New York, 1966.
- [22] H. SALARIEH AND A. ALASTY, *Control of stochastic chaos using sliding mode method*, J. Comput. Appl. Math. **225** (2009), 135–145.
- [23] J. A. SANDERS, F. VERHULST AND J. MURDOCK, *Averaging method in nonlinear dynamical systems*, Appl. Math. Sci., vol. **59**, Springer, New York, 2007.
- [24] M. S. SIEWE, F. M. KAKMENI AND C. TCHAWOUA, *Resonant oscillation and homoclinic bifurcation in $a\phi^6$ -Van der Pol oscillator*, Chaos, Solitons and Fractals **21**(4) (2004), 841–853.
- [25] W. SZEMPLINSKA-STUPNICKA AND J. RUDOWSKI, *Neimark bifurcation almost-periodicity and chaos in the forced Van der Pol–duffing system in the neighbourhood of the principal resonance*, Phys. Lett. A **192**(2–4) (1994), 201–206.
- [26] R. TCHOUKUEGNO, B. R. N. NBENDJO AND P. WOAFUO, *Resonant oscillations and fractal basin boundaries of a particle in a ϕ^6 -potential*, Physica A **304**(3–4) (2002), 362–378.
- [27] Y. UEDA AND N. AKAMATSU, *Chaotically transitional phenomena in the forced negative-resistance oscillator*, IEEE Trans. Circuits Syst. **28**(3) (1981), 217–224.
- [28] A. VENKATESAN AND M. LAKSHMANAN, *Bifurcation and chaos in the double-well Duffing–Van der Pol oscillator: numerical and analytical studies.*, Phys. Rev. E **56**(6) (1997), 6321–6330.
- [29] L. YANG, *Recent Advances on Determining the Number of Real Roots of Parametric Polynomials*, J. Symbolic Computation **28** (1999), 225–242.
- [30] X. YANG, W. XU AND Z. SUN, *Effect of Gaussian white noise on the dynamical behaviours of an extended Duffing–Van der Pol oscillator*, Internat. J. Bifur. Chaos Appl. Sci. Engrg. **16** **9** (2006), 2587–2600.
- [31] X. YANG, W. XU AND Z. SUN, *Effect of bounded noise on the chaotic motion of a Duffing Van der pol oscillator in a ϕ^6 oscillator*, Chaos, Solitons and Fractals **27** **3** (2006), 778–788.

APPENDIX A. ROOT CLASSIFICATION FOR A QUINTIC POLYNOMIAL

In this section we present a brief summary of the results about the number and multiplicities of the real/complex roots for a quintic polynomial with arbitrary coefficients presented in [29]. Indeed, consider the polynomial $P(x) = x^5 + px^3 + qx^2 + ux + v$. So, the following table gives the number of real and complex roots and multiplicities roots of $P(x)$ in all cases.

(1)	$D_5 > 0 \wedge D_4 > 0 \wedge D_3 > 0 \wedge D_2 > 0$	$\{1, 1, 1, 1, 1\}$
(2)	$D_5 > 0 \wedge (D_4 \leq 0 \vee D_3 \leq 0 \vee D_2 \leq 0)$	$\{1\}$
(3)	$D_5 < 0$	$\{1, 1, 1\}$
(4)	$D_5 = 0 \wedge D_4 > 0$	$\{2, 1, 1, 1\}$
(5)	$D_5 = 0 \wedge D_4 < 0$	$\{2, 1\}$
(6)	$D_5 = 0 \wedge D_4 = 0 \wedge D_3 > 0 \wedge E_2 \neq 0$	$\{2, 2, 1\}$
(7)	$D_5 = 0 \wedge D_4 = 0 \wedge D_3 > 0 \wedge E_2 = 0$	$\{3, 1, 1\}$
(8)	$D_5 = 0 \wedge D_4 = 0 \wedge D_3 < 0 \wedge E_2 \neq 0$	$\{1\}$
(9)	$D_5 = 0 \wedge D_4 = 0 \wedge D_3 < 0 \wedge E_2 = 0$	$\{3\}$
(10)	$D_5 = 0 \wedge D_4 = 0 \wedge D_3 = 0 \wedge D_2 \neq 0 \wedge F_2 \neq 0$	$\{3, 2\}$
(11)	$D_5 = 0 \wedge D_4 = 0 \wedge D_3 = 0 \wedge D_2 \neq 0 \wedge F_2 = 0$	$\{4, 1\}$
(12)	$D_5 = 0 \wedge D_4 = 0 \wedge D_3 = 0 \wedge D_2 = 0$	$\{5\}$

where

$$D_2 = -p,$$

$$D_3 = -12p^3 - 45q^2 + 40pu,$$

$$D_4 = -4p^3q^2 - 27q^4 + 12p^4u + 117pq^2u - 88p^2u^2 + 160u^3 - 40p^2qv - 300quv + 125pv^2,$$

$$D_5 = -4p^3q^2u^2 - 27q^4u^2 + 16p^4u^3 + 144pq^2u^3 - 128p^2u^4 + 256u^5 + 16p^3q^3v + 108q^5v - 72p^4quv - 630pq^3uv + 560p^2qu^2v - 1600qu^3v + 108p^5v^2 + 825p^2q^2v^2 - 900p^3uv^2 + 2250q^2uv^2 + 2000pu^2v^2 - 3750pqv^3 + 3125v^4,$$

$$E_2 = 16p^4q^2 - 48p^5u + 60p^2q^2u + 160p^3u^2 + 900q^2u^2 - 1100p^3qv - 3375q^3v + 1500pquv + 625p^2v^2,$$

$$F_2 = 3q^2 - 8pu.$$

The polynomials D_i , $i = 2, 3, 4, 5$, E_2 and F_2 form a discriminant system which is sufficient for the classification of roots of the polynomial $P(x)$, which is described by the right column of the table. For instance, $\{1, 1, 1\}$ means three real simple roots and a pair of complex roots, and $\{3, 1, 1\}$ means a real triple root plus two real simple roots.

¹ DEPARTAMENT DE MATEMÀTIQUES, UNIVERSITAT AUTÒNOMA DE BARCELONA, 08193 BELLATERRA, BARCELONA, CATALONIA, SPAIN

E-mail address: jllibre@mat.uab.cat

² DEPARTAMENT DE MATEMÁTICA, IBILCE, UNESP, RUA CRISTOVAO COLOMBO
2265, JARDIM NAZARETH, CEP 15.054-00, SAO JOSÉ DE RIO PRETO, SP, BRAZIL
E-mail address: rodrigo.euzebio@sjrp.unesp.br